

funkwerk D4 Office

The DECT handset for the business environment



funkwerk D4 Office

Replacement for the D3 mobile,
funktel FC1 and
GAP/CAP-compatible devices

Highlights:

- ▶ **Easy device exchange** by using the SIM-Card (MemCard) of the D3 / FC1 in the D4, data transfer of the D3 / FC1 registration data as well as the telephone directory is possible without technical support
- ▶ **GAP/CAP compatible:** system registration possible without SIM-Card (MemCard) by using internal IPEI
- ▶ **Interchangeable Lithium-ion battery:** modern battery technology for long stand-by times and extended battery life
- ▶ **High-contrast TFT display:** 16 Bit / 65.536 colours
- ▶ **Easy-to-use keypad** made of durable material
- ▶ **20 MIDI ring-tones and 10 signal tones:** melody and volume can be set separately for internal and external calls, suitable for high levels of ambient noise
- ▶ **Muting and vibrator function** can be activated by means of a soft key for discreet signalling, with locking of the messaging function indicating the alarm
- ▶ **Messaging funktion** with manual acknowledgement and priority-controlled signalling for clear differentiation of normal and alarm messages
- ▶ **Hotkeys for local telephone directory** for direct access to the desired entry
- ▶ **Call and received-call lists** as well as redial lists – 20 entries each
- ▶ **Loudspeaker** for hands-free calling
- ▶ **Key-lock:** manual and automatic
- ▶ **SOS function** by means of a soft key on a locked handset

funkwerk D4 Office

DECT™ office handset

The D4 Office handset was specially developed as a follow-up to the previous D3 / FC1 handsets as well as for use in the GAP / CAP environment. In addition to a contemporary design incorporating state-of-the-art battery technology and real-time telephony and messaging functions, particular emphasis was placed on an easy transition from old to new. In this way, after the user has transferred the SIM-Card (MemCard) from the previous D3 / FC1 to the D4 Office, the handset is ready for use immediately. This does not require any intervention by a technician, and the user can continue to access his local telephone directory.

Thanks to its slim design, light weight, clearly legible display and ergonomic keypad, the D4 Office is remarkably easy to use.

The D4 Office can be used in virtually all DECT systems.

Technical data DECT™- D4 Office handset		
Dimensions	L x B x H in mm	Approx. 141 x 47 x 20 * (with clip * approx. 141 x 47x 30)
	Weight (with battery)	Approx.: 106 g (with clip* 113g)
Temperature range:		
	Operating temperature range:	Operation: -10 ... +55 °C Charging: 0... +40°C
Power supply:	Li-ion interchangeable battery:	3,7 V / 650 mAh
	Charging time:	Approx. 5 hours
Handset operating time:	Standby:	Up to 150 hours**
	Talking:	Up to 17 hours**
DECT™-HF:	Frequency range:	1.88 ... 1,9 GHz
	Transmission power:	10mW; peak value 250 mW
Acoustics:	Acoustic signalling:	Up to 100 dB(A)*** At a distance of 30 cm
	Loudspeaker:	At the rear
	Hands-free:	Excellent voice quality
	Vibration alarm:	Additional or silent signalling


*) Accessories

**) with / without idle light

***) According to selected ring tone,
suitable for use in noisy environments



Accessories for funkwerk D4 Office	
Charger and batteries:	Single charger
	Comfort charger for additional battery charging
	Spare battery
Bags:	Leather bag, holster with belt-loop
	Protective bag, closed, with window
Belt clip:	sturdy design, screwed on



SIM-Card (MemCard)

In the D3 / FC1, the registration data and the telephone directory are stored on a separate memory card, allowing it easily to be transferred from a predecessor device to a D4 Office.

Funkwerk Security Communications GmbH
John-F.-Kennedy-Str. 43-53
D-38228 Salzgitter
Telefon: +49-5341 - 2235-0
Telefax: +49-5341 - 2235-709
www.funkwerk-sc.com